

S6: 838 - 865 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10	Group 11	Group 12	Group 13	Group 14	Group 15
1	838,200	838,150	838,550	854,200	855,475	855,075	854,750	854,750	854,425	863,200	838,200	838,900	838,100	838,700	838,400
2	841,450	839,375	839,775	855,300	857,425	857,775	855,850	855,850	855,525	864,500	839,900	842,600	841,100	842,800	840,600
3	843,275	841,300	841,700	856,700	860,600	860,725	857,250	857,250	857,400		841,000	845,900	842,700	844,800	842,100
4	846,225	842,475	842,875	857,800			858,350	858,350	858,500		842,375	847,500	847,000	846,300	844,700
5	847,350	846,400	846,800	859,675			860,225	860,225	859,900		844,400	848,600	849,200	847,400	846,600
6	850,125	848,025	848,425	860,775			861,325	861,325	861,000		846,100	850,100	850,400	849,200	848,100
7	852,575	850,025	850,425								847,350	852,100	852,500	851,300	850,700
8	854,575	852,475	852,875								849,400	853,300	854,100		851,850
9	856,200	855,250	855,650								851,800	855,100	855,300		853,700
10	860,125	856,375	856,775								853,200	857,200			
11	861,300	859,325	859,725									858,650			
12	863,225	861,150	861,550									859,800			
13	864,450	864,400	864,800									861,900			
	Full Range max. # of compatible frequencies (option 1)	Full Range max. # of compatible frequencies (option 2)	Full Range max. # of compatible frequencies (option 3)	BEL / TUR preferred: opt. TV ch.69 854-862 MHz	U.K. preferred: "CH69 Co-ordinated" SET 1	U.K. preferred: "CH69 Co-ordinated" SET 3	U.K. preferred: "Co-ordinated frequencies" INDOORS	U.K. preferred: "Co-ordinated frequencies" OUTDOORS (option 1)	U.K. preferred: "Co-ordinated frequencies" OUTDOORS (option 2)	European harmonized band: optimized for 863 - 865 MHz	Compatible setup for use with EUT-TW-TZ (S6 > TW-TZ)	Compatible setup for use with EUT-VR-VT (S6 > VR-VT)	Compatible setup for use with PSM400-KE (S6 > KE)	Compatible setup for use with PSM400-KE (S6 = KE)	Compatible setup for use with PSM200-S5 (S6 > S5)